

# 5.3 DMX512 Configuration


1/4 channel mode:

DMX 512 Configuration						
1-CH mode	4-CH mode					
Shows	Ch1	Ch2			Ch3	Ch4
	Mode	2-1(Line effect)	2-2(Number)	2-3(Letter)	Dimmer	Strobe
<b>248-255 Stand alone</b>	255	248-255 Random line effect	236-255 To count forwards 9	247-255 Letter-Z		248-255 Open
<b>218-247 Show 8</b>	248-255 Auto	240-247 effect30 slow to fast	down to 0 from slow to fast	238-246 Letter-Y		248-255 Auto
<b>188-217 Show 7</b>	188-247 Letter A to Z (see channel 2-3)	232-239 effect 29 slow to fast	216-235 To count forwards 0 up to 9 from slow to fast	229-237 Letter-X		240-247 Open
<b>158-187 Show 6</b>	128-187 Number 1 to 9 (see channel 2-2)	224-231 effect 28 slow to fast	196-215 Number-9	220-228 Letter-W		232-239 Open
<b>128-157 Show 5</b>	68-127 Effect (see Channel 2-1)	216-223 effect 27 slow to fast	176-195 Number-8	211-219 Letter-V		190-231 Fast open slow close
<b>098-127 Show 4</b>	8-67 Full On	208-215 effect 26 slow to fast	156-175 Number-7	202-210 Letter-U		182-189 Open
<b>068-097 Show 3</b>	0-7 Blackout	200-207 effect25 slow to fast	136-155 Number-6	193-201 Letter-T		140-181 Slow open fast close
<b>038-067 Show 2</b>		192-199 effect24 slow to fast	116-135 Number-5	184-192 Letter-S		132-139 Open
<b>008-037 Show 1</b>		184-191 effect23 slow to fast	096-115 Number-4	175-183 Letter-R		
<b>000-007 Blackout</b>		176-183 effect22 slow to fast	076-095 Number-3	166-174 Letter-Q		8-131 Strobe slow to fast
		168-175 effect21 slow to fast	056-075 Number-2	157-165 Letter-P		
		160-167 effect20 slow to fast	036-055 Number-1	148-156 Letter-O		0-7 Open
		152-159 effect19 slow to fast	016-035 Number-0	139-147 Letter-N		
		144-151 effect18 slow to fast	000-015 No function	130-138 Letter-M		
		136-143 effect17 slow to fast		121-129 Letter-L		
		128-135 effect16 slow to fast		112-120 Letter-K		
		120-127 effect15 slow to fast		103-111 Letter-J		
		112-119 effect14 slow to fast		094-102 Letter-I		
		104-111 effect13 slow to fast		085-093 Letter-H		
		096-103 effect12 slow to fast		076-084 Letter-G		
		088-095 effect11 slow to fast		067-075 Letter-F		
		080-087 effect10 slow to fast		058-066 Letter-E		
		072-079 effect09 slow to fast		049-057 Letter-D		
		064-071 effect08 slow to fast		040-048 Letter-C		
		056-063 effect07 slow to fast		031-039 Letter-B		
		048-055 effect06 slow to fast		022-030 Letter-A		
		040-047 effect05 slow to fast		000-021 No function		
		032-039 effect04 slow to fast				
		024-031 effect03 slow to fast				
		016-023 effect02 slow to fast				
		008-015 effect01 slow to fast				
		000-007 no function				

9 channel mode:

9-CH mode					
Ch1	Ch2	Ch3	Ch4	Ch5	
Dimmer (LED1-5)	Dimmer (LED6-10)	Dimmer (LED11-15)	Dimmer (LED16-20)	Dimmer (LED21-25)	
Ch6	Ch7			Ch8	Ch9
Mode	2-1(Line effect)	2-2(Number)	2-3(Letter)	Dimmer (All)	Strobe
248-255 Auto 188-247 Letter A to Z (see channel 2-3) 128-187 Number 1 to 9 (see channel 2-2) 068-127 Effect (see Channel 2-1) 045-067 Dimmer All Dimmer Ch1 Control LED1.6, 11.16.21 Ch2 Control LED2.7, 12.17.22 022-044 Ch3 Control LED3.8, 13.18.23 Ch4 Control LED4.9, 14.19.24 Ch5 Control LED5.10, 15.20.25 000-021 Dimmer Ch1 Control LED1-5 Ch2 Control LED6-10 Ch3 Control LED11-15 Ch4 Control LED16-20 Ch5 Control LED21-25	248-255 Random line effect 240-247 effect30 slow to fast 232-239 effect 29 slow to fast 224-231 effect 28 slow to fast 216-223 effect 27 slow to fast 208-215 effect 26 slow to fast 200-207 effect25 slow to fast 192-199 effect24 slow to fast 184-191 effect23 slow to fast 176-183 effect22 slow to fast 168-175 effect21 slow to fast 160-167 effect20 slow to fast 152-159 effect19 slow to fast 144-151 effect18 slow to fast 136-143 effect17 slow to fast 128-135 effect16 slow to fast 120-127 effect15 slow to fast 112-119 effect14 slow to fast 104-111 effect13 slow to fast 096-103 effect12 slow to fast 088-095 effect11 slow to fast 080-087 effect10 slow to fast 072-079 effect09 slow to fast 064-071 effect08 slow to fast 056-063 effect07 slow to fast 048-055 effect06 slow to fast 040-047 effect05 slow to fast 032-039 effect04 slow to fast 024-031 effect03 slow to fast 016-023 effect02 slow to fast 008-015 effect01 slow to fast 000-007 no function	236-255 To count forwards 9 down to 0 from slow to fast 216-235 To count forwards 0 up to 9 from slow to fast 196-215 Number-9 176-195 Number-8 156-175 Number-7 136-155 Number-6 116-135 Number-5 096-115 Number-4 076-095 Number-3 056-075 Number-2 036-055 Number-1 016-035 Number-0 000-015 No function	247-255 Letter-Z 238-246 Letter-Y 229-237 Letter-X 220-228 Letter-W 211-219 Letter-V 202-210 Letter-U 193-201 Letter-T 184-192 Letter-S 175-183 Letter-R 166-174 Letter-Q 157-165 Letter-P 148-156 Letter-O 139-147 Letter-N 130-138 Letter-M 121-129 Letter-L 112-120 Letter-K 103-111 Letter-J 094-102 Letter-I 085-093 Letter-H 076-084 Letter-G 067-075 Letter-F 058-066 Letter-E 049-057 Letter-D 040-048 Letter-C 031-039 Letter-B 022-030 Letter-A 000-021 No function		248-255 Open 240-247 Auto 232-239 Open 190-231 Fast open slow close 182-189 Open 140-181 Slow open fast close 132-139 Open 008-131 000-007 Open

25 channel mode:



29 channel mode:

DMX 512 Configuration												
29-CH mode												
Ch1	Ch2	Ch3	Ch4	Ch5	Ch6	Ch7	Ch8	Ch9	Ch10	Ch11	Ch12	Ch13
Dimmer1	Dimmer2	Dimmer3	Dimmer4	Dimmer5	Dimmer6	Dimmer7	Dimmer8	Dimmer9	Dimmer10	Dimmer11	Dimmer12	Dimmer13
Ch14	Ch15	Ch16	Ch17	Ch18	Ch19	Ch20	Ch21	Ch22	Ch23	Ch24	Ch25	
Dimmer14	Dimmer15	Dimmer16	Dimmer17	Dimmer18	Dimmer19	Dimmer20	Dimmer21	Dimmer22	Dimmer23	Dimmer24	Dimmer25	
Ch26	Ch27			Ch28	Ch29							
Mode	2-1(Line effect)	2-2(Number)	2-3(Letter)	Dimmer	Strobe							
<p>255</p> <p>248-255 Auto</p> <p>188-247 Letter A to Z (see channel 2-3)</p> <p>128-187 Number 1 to 9 (see channel 2-2)</p> <p>68-127 Effect (see channel 2-1)</p> <p>8-67 Full On</p> <p>0-7 Blackout</p> <p>0</p>	<p>248-255 Random line effect</p> <p>240-247 effect30 slow to fast</p> <p>232-239 effect29 slow to fast</p> <p>224-231 effect28 slow to fast</p> <p>216-223 effect27 slow to fast</p> <p>208-215 effect26 slow to fast</p> <p>200-207 effect25 slow to fast</p> <p>192-199 effect24 slow to fast</p> <p>184-191 effect23 slow to fast</p> <p>176-183 effect22 slow to fast</p> <p>168-175 effect21 slow to fast</p> <p>160-167 effect20 slow to fast</p> <p>152-159 effect19 slow to fast</p> <p>144-151 effect18 slow to fast</p> <p>136-143 effect17 slow to fast</p> <p>128-135 effect16 slow to fast</p> <p>120-127 effect15 slow to fast</p> <p>112-119 effect14 slow to fast</p> <p>104-111 effect13 slow to fast</p> <p>096-103 effect12 slow to fast</p> <p>088-095 effect11 slow to fast</p> <p>080-087 effect10 slow to fast</p> <p>072-079 effect09 slow to fast</p> <p>064-071 effect08 slow to fast</p> <p>056-063 effect07 slow to fast</p> <p>048-055 effect06 slow to fast</p> <p>040-047 effect05 slow to fast</p> <p>032-039 effect04 slow to fast</p> <p>024-031 effect03 slow to fast</p> <p>016-023 effect02 slow to fast</p> <p>008-015 effect01 slow to fast</p> <p>000-007 no function</p>	<p>236-255 To count forwards 9 down to 0 from slow to fast</p> <p>216-235 To count forwards 0 up to 9 from slow to fast</p> <p>196-215 Number-9</p> <p>176-195 Number-8</p> <p>156-175 Number-7</p> <p>136-155 Number-6</p> <p>116-135 Number-5</p> <p>096-115 Number-4</p> <p>076-095 Number-3</p> <p>056-075 Number-2</p> <p>036-055 Number-1</p> <p>016-035 Number-0</p> <p>000-015 No function</p>	<p>247-255 Letter-Z</p> <p>238-246 Letter-Y</p> <p>229-237 Letter-X</p> <p>220-228 Letter-W</p> <p>211-219 Letter-V</p> <p>202-210 Letter-U</p> <p>193-201 Letter-T</p> <p>184-192 Letter-S</p> <p>175-183 Letter-R</p> <p>166-174 Letter-Q</p> <p>157-165 Letter-P</p> <p>148-156 Letter-O</p> <p>139-147 Letter-N</p> <p>130-138 Letter-M</p> <p>121-129 Letter-L</p> <p>112-120 Letter-K</p> <p>103-111 Letter-J</p> <p>094-102 Letter-I</p> <p>085-093 Letter-H</p> <p>076-084 Letter-G</p> <p>067-075 Letter-F</p> <p>058-066 Letter-E</p> <p>049-057 Letter-D</p> <p>040-048 Letter-C</p> <p>031-039 Letter-B</p> <p>022-030 Letter-A</p> <p>000-021 No function</p>	<p>255</p> <p>100%</p> <p>0%</p>	<p>255</p> <p>Open</p> <p>248-255 Auto</p> <p>240-247 Auto</p> <p>232-239 Open</p> <p>190-231 Fast open slow close</p> <p>182-189 Open</p> <p>140-181 Slow open fast close</p> <p>132-139 Open</p> <p>8-131 Strobe slow to fast</p> <p>0-7 Open</p> <p>0</p>							