

DMX MASTER I/II

CA-1612J/CA-1612W



Features

- Reliable, advanced universal DMX 512 controllers control up to 192 channels
- Control 12 fixtures with 16 channels per fixture
- 30 banks, each bank has 8 scenes, and 240 scenes in total
- 6 programmable chases with fade time and speed
- DMX signal can remote control addressing
- Fog control button
- The setting data of controller can be transmitted from one fixture to another fixture
- Blackout, tap sync, and manual override
- DMX polarity selector
- Fine adjustment of the Pan and Tilt
- Exclusive joystick for controlling PAN/TILT(CA-1612J)
- Assignable and reversible jog wheels(CA-1612W)



Electrical and Physical

- Power Voltage: DC 9~12V, 300mA min
 - DMX Output: 3 pin female XLR
 - Dimension(mm): 3U19",483x132x73mm , 2.5Kg
 - Dimension(in): 3U19",19.0"x5.1"x2.8" in, 5.5lbs
-