

7 Channels (Mode 1):

CHANNEL	VALUE	FUNCTION
1	000-007	CCT 6000K
	008-048	5600K
	049-089	5000K
	090-130	4500K
	131-171	4000K
	172-212	3200K
	213-255	2700K
2	000-007	COLOR WHEEL Open
	008-016	Color 1
	017-025	Color 2
	026-034	Color 3
	035-043	Color 4
	044-052	Color 5
	053-063	Color 6
	064-127	Open
	128-189	Clockwise Rotation, Fast to Slow
	190-193	Stop
	194-255	Counter-Clockwise Rotation, Slow to Fast
3	000-015	MINUS GREEN 0
	016-031	1/2
	032-047	1/4
	048-063	1/8
	064-255	Null
4	000-255	ZOOM Narrow→Wide
5	000-255	FOCUS 0%→100%
6	000-007	STROBE Close
	008-015	Open
	016-131	Strobe from Slow to Fast
	132-139	Open
	140-181	Fast Open Slow Close from Slow to Fast
	182-189	Open
	190-231	Slow Open Fast Close from Slow to Fast

	232-239 240-247 248-255	Open Random Strobe from Slow to Fast Open
7	000-255	DIMMER 0%→100%

