

57 Channels (Mode 1):

CHANNEL	VALUE	FUNCTION
1	000-255	Tilt 0°→220°
2	000-255	Tilt Fine
3	000-007 008-247 248-255	Tilt Speed auto speed slow to fast auto speed
4	000-255	Zoom 1 0%→100%
5	000-255	Zoom 2 0%→100%
6	000-255	Dimmer 0%→100%
7	000-255	Dimmer Fine
8	000-031 032-063 064-095 096-127 128-159 160-191 192-223 224-255	Strobe Closed Open Strobe from fast to slow Open Pulse-effect in sequences Open Random strobe from slow to fast Open
9	000-255	LED1 RED 0%→100%
10	000-255	LED1 GREEN 0%→100%
11	000-255	LED1 BLUE 0%→100%
12	000-255	LED1 WHITE 0%→100%
13	000-255	LED2 RED 0%→100%
14	000-255	LED2 GREEN 0%→100%
15	000-255	LED2 BLUE

		0%→100%
16	000-255	LED2 WHITE 0%→100%
17	000-255	LED3 RED 0%→100%
18	000-255	LED3 GREEN 0%→100%
19	000-255	LED3 BLUE 0%→100%
20	000-255	LED3 WHITE 0%→100%
21	000-255	LED 4RED 0%→100%
22	000-255	LED4 GREEN 0%→100%
23	000-255	LED4 BLUE 0%→100%
24	000-255	LED4 WHITE 0%→100%
25	000-255	LED5 RED 0%→100%
26	000-255	LED5 GREEN 0%→100%
27	000-255	LED5 BLUE 0%→100%
28	000-255	LED5 WHITE 0%→100%
29	000-255	LED6 RED 0%→100%
30	000-255	LED6 GREEN 0%→100%
31	000-255	LED6 BLUE 0%→100%
32	000-255	LED6 WHITE 0%→100%
33	000-255	LED7 RED 0%→100%
34		LED7 GREEN

	000-255	0%→100%
35	000-255	LED7 BLUE 0%→100%
36	000-255	LED7 WHITE 0%→100%
37	000-255	LED8 RED 0%→100%
38	000-255	LED8 GREEN 0%→100%
39	000-255	LED8 BLUE 0%→100%
40	000-255	LED8 WHITE 0%→100%
41	000-255	LED9 RED 0%→100%
42	000-255	LED9 GREEN 0%→100%
43	000-255	LED9 BLUE 0%→100%
44	000-255	LED9 WHITE 0%→100%
45	000-255	LED10 RED 0%→100%
46	000-255	LED10 GREEN 0%→100%
47	000-255	LED10 BLUE 0%→100%
48	000-255	LED10WHITE 0%→100%
49	000-255	LED11 RED 0%→100%
50	000-255	LED11 GREEN 0%→100%
51	000-255	LED11 BLUE 0%→100%
52	000-255	LED11 WHITE 0%→100%
53		LED12 RED

	000-255	0%→100%
54	000-255	LED12 GREEN 0%→100%
55	000-255	LED12 BLUE 0%→100%
56	000-255	LED12 WHITE 0%→100%
57	000-060 061-080 081-100 101-120 121-140 141-160 161-180 181-200 201-220 221-240 241-255	Special Function No function Blackout when tilt moving enable Blackout when tilt moving disable Reset All Reset Tilt Reset Zoom Dimmer Speed: Smooth Dimmer Speed: Fast Invert Pixel Order: No Invert Pixel Order: Yes No Function

14 Channels (Mode 2):

CHANNEL	VALUE	FUNCTION
1	000-255	Tilt 0°→220°
2	000-255	Tilt Fine
3	000-255	Zoom 0%→100%
4	000-255	Dimmer 0%→100%
5	000-255	Dimmer Fine
6	000-031 032-063 064-095 096-127 128-159 160-191 192-223	Strobe Closed Open Strobe from fast to slow Open Pulse-effect in sequences Open Random strobe from slow to fast

	224-255	Open
7	000-008 009-038 039-068 069-098 099-128 129-158 159-187 188-255	Macro No function macro1 macro2 macro3 macro4 macro5 macro6 macro7
8	000-255	Foreground Color 0%→100%
9	000-255	Background Color 0%→100%
10	000-255	RED 0%→100%
11	000-255	GREEN 0%→100%
12	000-255	BLUE 0%→100%
13	000-255	WHITE 0%→100%
14	000-060 061-080 081-100 101-120 121-140 141-160 161-180 181-200 201-220 221-240 241-255	Special Function No function Blackout when tilt moving enable Blackout when tilt moving disable Reset All Reset Tilt Reset Zoom Dimmer Speed: Smooth Dimmer Speed: Fast Invert Pixel Order: No Invert Pixel Order: Yes No Function

9+ Channels (Mode 3):

CHANNEL	VALUE	FUNCTION
Controlled by DMX		
1	000-255	Tilt 0°→220°
2	000-255	Tilt Fine
3	000-007 008-247 248-255	Tilt Speed auto speed slow to fast auto speed
4	000-255	Zoom 1 0%→100%
5	000-255	Zoom 2 0%→100%
6	000-255	Dimmer 0%→100%
7	000-255	Dimmer Fine
8	000-031 032-063 064-095 096-127 128-159 160-191 192-223 224-255	Strobe Closed Open Strobe from fast to slow Open Pulse-effect in sequences Open Random strobe from slow to fast Open
9	000-060 061-080 081-100 101-120 121-140 141-160 161-180 181-200 201-220 221-240 241-255	Special Function No function Blackout when tilt moving enable Blackout when tilt moving disable Reset All Reset Tilt Reset Zoom Dimmer Speed: Smooth Dimmer Speed: Fast Invert Pixel Order: No Invert Pixel Order: Yes No Function

Controlled by Art-Net		
1	000-255	LED1 RED 0%→100%
2	000-255	LED1 GREEN 0%→100%
3	000-255	LED1 BLUE 0%→100%
4	000-255	LED1 WHITE 0%→100%
5	000-255	LED2 RED 0%→100%
6	000-255	LED2 GREEN 0%→100%
7	000-255	LED2 BLUE 0%→100%
8	000-255	LED2 WHITE 0%→100%
9	000-255	LED3 RED 0%→100%
10	000-255	LED3 GREEN 0%→100%
11	000-255	LED3 BLUE 0%→100%
12	000-255	LED3 WHITE 0%→100%
13	000-255	LED 4RED 0%→100%
14	000-255	LED4 GREEN 0%→100%
15	000-255	LED4 BLUE 0%→100%
16	000-255	LED4 WHITE 0%→100%
17	000-255	LED5 RED 0%→100%
18	000-255	LED5 GREEN 0%→100%
19		LED5 BLUE

	000-255	0%→100%
20	000-255	LED5 WHITE 0%→100%
21	000-255	LED6 RED 0%→100%
22	000-255	LED6 GREEN 0%→100%
23	000-255	LED6 BLUE 0%→100%
24	000-255	LED6 WHITE 0%→100%
25	000-255	LED7 RED 0%→100%
26	000-255	LED7 GREEN 0%→100%
27	000-255	LED7 BLUE 0%→100%
28	000-255	LED7 WHITE 0%→100%
29	000-255	LED8 RED 0%→100%
30	000-255	LED8 GREEN 0%→100%
31	000-255	LED8 BLUE 0%→100%
32	000-255	LED8 WHITE 0%→100%
33	000-255	LED9 RED 0%→100%
34	000-255	LED9 GREEN 0%→100%
35	000-255	LED9 BLUE 0%→100%
36	000-255	LED9 WHITE 0%→100%
37	000-255	LED10 RED 0%→100%
38		LED10 GREEN

	000-255	0%→100%
39	000-255	LED10 BLUE 0%→100%
40	000-255	LED10WHITE 0%→100%
41	000-255	LED11 RED 0%→100%
42	000-255	LED11 GREEN 0%→100%
43	000-255	LED11 BLUE 0%→100%
44	000-255	LED11 WHITE 0%→100%
45	000-255	LED12 RED 0%→100%
46	000-255	LED12 GREEN 0%→100%
47	000-255	LED12 BLUE 0%→100%
48	000-255	LED12 WHITE 0%→100%